

## IH8075 - HOMEGUARD



IH8075 – MS8000

### For small apartments and studios

#### Key Features

- Built-in 180° PIR sensor with 6 metre range
- Arm/Disarm with keyfob (up to 4) and by PIN code
- Alarm tripped by PIR or panic on the keyfob.
- Built-in telephone dialler to call up to 3 numbers.
- Wall mounted or desktop.

#### Use & Applications

All that you need to protect small apartments, studios or garages Simple to install and also discrete but attractive. Just plug the power supply into the nearest power socket and the telephone cable into the nearest telephone socket. The unit is ready. All you need to do to arm the system is to key the PIN code.

If a burglar is detected by the built-in PIR, the telephone dialler will call for help and the siren will scream. When you have gone away, knowing that your home is being looked after 24 hours is real peace of mind.

Even when you are at home, you can have additional security with the panic function, provided by the key fob.

#### Technical information

- Coverage area movement detector : 110° of arc / 12 meters radius
- Operating voltage : 230V/50hz - 12V mains adapter plug
- Emergency power battery : 9 V block battery
- 20 Std. standby with Lithium battery
- 12 Std. standby with Alkaline battery
- Automatic telephone : Analogue dialling unit
- Dialling unit : 3 telephone numbers, each with a max. of 16 digits
- 9 seconds permanently recorded alarm text
- Sirens : 95 dB/1m, can be switched off
- Access code: Set in the factory at 0000, can be changed to any other 4-digit number
- Remote control units: Maximum of 4 Key chain remotes (IH8040) can be used.
- External input: for triggering the automatic telephone dialling unit via a non-voltage contact
- LEDs: 2, for displaying status